

Model NSR22-BM Belt Misalignment Switches

Specifications

The Model NSR22-BM Belt misalignment switches are conveyor safety accessories designed to alarm and/or shut down conveyor systems in the event of a conveyor belt misalignment. The heavy duty rugged design makes them suitable for most industrial applications. The body structure is covered with aluminum cast static paint, it is resistant to corrosion. Shaft and arm mechanisms are made of stainless steel. The handle mechanism is cylindrical in structure and operates with two bearings. NSR22-BM Belt Misalignment Switches, It is mounted on both sides of the conveyor belt to be attached to the chassis. It is designed to prevent damage to the belts and equipment due to the misalignment of the conveyor belt. System decreases downtime and maintenance costs and time can be saved. The roller arm of the switch is placed about 15cm away from the normal belt position. If the belt begins to

wander, it makes contact with the roller arm causing it to spin. As more force is applied to the roller arm it will rotate away from the normal position and at 15° it will actuate the first alarm micro switch. The first micro switch will announce the alarm condition to the control system so corrective action can be taken. If the belt continues to slip, the system is stopped by activating the second micro switch at 30° position. The alarm contact structure is available on request. It can be used with only one contact mechanism without using alarm contact. The micro switch used in the products is approved by VDE. All products are produced as accordance with CE standards. Also It meets EAC standards for the Russian market. NSR22-BM series products do not require any maintenance.

Technical Specifications

- Body : Aluminum Casting
- Micro Switch Values : 400VAC 6A / 230VAC 8A / 24VDC 10A →
- Output Signal : (1) SPDT shutdown, alarm can be added upon request.
- Cable Entry : 2xM25
- Temperature Rating : -55°C - +100°C
- Movement Angle : 15° and 35°
- Contact Status : Snap - Action
- Protection Class : IP68
- Casing Color : Red (RAL 3020)
- Weight : 3.9 Kg
- Mounting Structure : It is suitable for double-sided use.

Options

- EX - Zone 22 / Zone 21
- Reset Cancellation
- Bus Security Interface
- Adjustable Angle
- Bmc Hard Composite Body
- Mounting Feet
- Arm Length and Diameter

Security Approvals:

Electrical Security	EN60947
Mechanical Security	EN 60204
Outdoor Security	EN 60529
Current Certificate	CE
Russia Market	EAC
Micro Switch	VDE
Explosive Environment	EX - Zone 22 / Zone 21

Model Specifications List

Model	Alarm			Stop			Reset
	NC	NO	Angle	NC	NO	Angle	
NSR22-BM			15°	1	1	35°	Available
NSR22-BM-A01			15°	1	1	35°	**
NSR22-BM-A11	1	1	15°	1	1	35°	Available
NSR22-BM-A11B	1	1	15°	1	1	35°	**
NSR22-BM-22			15°	2	2	35°	Available
NSR22-BM-A02			15°	2	2	35°	**
NSR22-BM-A22	2	2	15°			35°	Available
NSR22-BM-A22B	2	2	15°			35°	**
NSR22-BM-33			15°	3	3	35°	Available
NSR22-BM-A03			15°	3	3	35°	**
NSR22-BM-A33	3	3	15°			35°	Available
NSR22-BM-A33B	3	3	15°			35°	**

Spare Parts Accessories List

Model	Features
KB-826	1NO+1NC Switch
KB-826-2	2NO+2NC Switch
KB-826-3	3NO+3NC Switch
KB-R-01	M25x1,5 Cable Gland
KB-KT-01	M25 Blind Plug
KB-4-KN	4 Pin Connector
BA-11	Connection Mounting Foot
KB-NGV-01	Body Cover
TSR-42-BM-EX	Bearing Stainless Arm
KB-PM	Reset Lever

Please review the manual file for product use. Check the KBT Accessory catalog for mounting the products on the belt.

